

Metra Power Clamp 1000A/400A

Digital clamp meter



Application

Metra Power Clamp 1000A/400A measures, calculate and displays important electrical parameters of single phase or three phase power system. It also features Resistance, continuity, diode and non contact voltage detection.

Product Features:

- Measures following parameters
- AC & DC Voltage up to 1000V
- AC & DC Current up to 1000A /400 A
- Inrush/Peak Value Measurement
- Active, Reactive and Apparent Power
- Horse Power Measurement
- kWh
- Measure up to 49th Harmonics
- Phase Angle
- THD
- DF
- Power Factor
- Crest Factor
- LPF Mode for VFD Application
-

Unique Design

Metra Power Clamp 1000A/400A is a highly innovative design for features those increases safety and comfort of user.

- Rotating clamp jaws facilitate the measurement at physically awkward positions, vertical bus bars, conductors placed at positions difficult to access.
- Clamp jaws can be opened or closed with the trigger placed at bottom side away from the jaws. This allows the user to place his/her hand at safer distance from live conductor. This greatly reduces exposure of human beings to electrical shocks.
- Location and design of trigger eliminates fatigues caused by single finger operation. It allows spreading the force required to open the jaws over more than one finger to ensure comfortable operation.
- Comfortable operation of push buttons and function selector switch, in adverse field conditions
-

Large Jaw Opening

Jaw opening of 51mm and 41 mm for standard wire diameter of 50mm and 40mm for 1000A and 400A respectively.

Inrush Current Measurement

Inrush current measurement
Clamp meter will be triggered by inrush current >5A. Inrush current for 100 msec is measured.

DATA Hold Function

By pressing DATA HOLD button, reading on the display can be latched for Hands free operation.

MIN,MAX Function

By pressing MIN/MAX button, the clamp meter will start recording latest Minimum and Maximum readings

Backlit

It is possible to conduct measurement using the clamp meter during poor light condition with the help of bright white light Backlit.

Non Contact Voltage Detection

The clamp meter can detect the presence of AC Voltage between 100 to 1000 V 50hz/60Hz

without any electrical connection and give acoustic signal as an indication.

Three Phase Power Measurement

Clamp meter can measure power in 3 phase 3 wire or 3 phase 4 wire (Symmetric as well as Asymmetric) network without any manual calculation like other clamp meters.

Dual Display

User friendly dual display shows the simultaneous parameters of measuring input quantity.

LPF Mode

LPF mode is available for voltage and current for true measurement of VFD Application

TRMS Measurement

In order to calculate true value of distorted waveform due to presence of high crest factor or harmonics, TRMS measurements is done for AC voltage and current

Auto Power OFF

In order to save the power of the Batteries, the clamp meter will automatically shut OFF if it detects no activity for 10 minutes.

Continuous ON Mode

In this mode, AUTO POWER OFF is disabled.

Low Battery Indication

Double molded Cover for soft touch and firm grip of the Instrument

Influence quantities and variations

Influence quantity	Range of influence	Measured quantity/ measuring range	Variation
Temperature	0 °C...21 °C and +25 °C...+50°C	V AC	0,15 x Intrinsic Error / °C
		V DC	
		V ACDC	
		A AC	
		A DC	
		A ACDC	
		AC Power	
		DC Power	
		Resistance/Diode/Continuity	
Frequency of the measured quantity	40 Hz...50 Hz and 60 Hz...400 Hz	V AC	1 X Intrinsic Error
		V ACDC	
		A AC	
		A ACDC	
	45 Hz...65 Hz ²	AC power	
Crest factor ¹	1,4...2	V AC A AC	1% + Intrinsic Error
	2...2,5		2.5% + Intrinsic Error
	2,5...5		4% + Intrinsic Error
Supply Voltage	When Low Battery symbol is ON	All Ranges	1 X Intrinsic Error
Relative humidity	75 %	All Ranges	1 X Intrinsic Error

1) Except SineWave

- CF 2 @ 690V, 690A for Power Clamp Meter 1000 A ACDC
- CF 3 @ 690V, 186A for Power Clamp Meter 400 A ACDC
- CF 4 @ 345V, 345A for Power Clamp Meter 1000 A ACDC
- CF 4 @ 345V, 140A for Power Clamp Meter 400 A ACDC
- CF 2 @ 690V, 280A for Power Clamp Meter 400 A ACDC
- CF 5 @ 280V, 280A for Power Clamp Meter 1000 A ACDC
- CF 3 @ 460V, 460A for Power Clamp Meter 1000 A ACDC
- CF 5 @ 280V, 112A for Power Clamp Meter 400 A ACDC

2) Except for 50 or 60 Hz

Technical Specification

Measuring function	Measuring range	Resolution	Intrinsic error of digital display at reference condition		Over load capacity	Overload duration		
			Over load value	Over load duration				
V DC	999.9 V	0.1 V	$\pm(0.5\% \text{ of rdg} + 5 \text{ dgt})$		1000 V DC/AC Eff/Sine wave	Continously		
V ~	999.9 V	0.1 V	$\pm(0.75\% \text{ of rdg} + 5 \text{ dgt})$					
V ACDC	999.9 V	0.1 V	$\pm(1.25\% \text{ of rdg} + 10 \text{ dgt})$					
LPF V~	999.9 V	0.1 V	50.....60 Hz	$\pm(0.75\% \text{ of rdg} + 5 \text{ dgt})$				
			61...400Hz	$\pm(5.0\% \text{ of rdg} + 5 \text{ dgt})$				
POWER CLAMP 1000A ADC-AAC	999.9 A	0.1 A	$\pm(1.5\% \text{ of rdg} + 5 \text{ dgt})^1$		1100 A AC/DC for power clamp 1000 A 440 A AC/DC For power clamp 400 A	Continously		
POWER CLAMP 400A ADC-AAC	99,99 A	0,01 A	display value <1000 add 10 dgt	$\pm(1.5\% \text{ of rdg} + 0.2 \text{ A})^1$				
	400 A	0,1 A		$\pm(1.5\% \text{ of rdg} + 5 \text{ dgt})^1$				
POWER CLAMP 1000 A ACDC	999,9 A	0,1 A	$\pm(3\% \text{ of rdg} + 10 \text{ dgt})^1$					
POWER CLAMP 400A A ACDC	99,99 A	0,01 A	display value <1000 add 10 dgt	$\pm(3\% \text{ of rdg} + 0.4 \text{ A})^1$				
	400 A	0,1 A		$\pm(3\% \text{ of rdg} + 10 \text{ dgt})^1$				
POWER CLAMP LPF 1000A A AC	999,99 A	0,1 A	50....60 Hz 61...400Hz	$\pm(1.5\% \text{ of rdg} + 5 \text{ dgt})$ $\pm(5.0\% \text{ of rdg} + 5 \text{ dgt})$	1000 V DC/AC 1100 A AC/DC for Power clamp 1000A 440 A AC/DC for Power clamp 400 A	Continously		
POWER CLAMP LPF 400A A AC	99,99 A	0,01 A		$\pm(1.5\% \text{ of rdg} + 0.3 \text{ A})$ $\pm(5.0\% \text{ of rdg} + 5 \text{ dgt})$				
	400 A	0,1 A		$\pm(1.5\% \text{ of rdg} + 5 \text{ dgt})$ $\pm(5.0\% \text{ of rdg} + 5 \text{ dgt})$				
Active Power ²	9,999 kW	1 W		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
	99,99 kW	10 W		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
	999,9 kW	100 W		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
	9999 kW	1 kW		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
Reactive Power ²	9,999 kVAr	1 VAr		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$		Continously		
	99,99 kVAr	10 VAr		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
	999,9 kVAr	100 VAr		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
	9999 kVAr	1 kVAr		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
Apparent Power ²	9,999 kVAr	1 VA		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$		1000 V DC/AC 1100 A AC/DC for Power clamp 1000A 440 A AC/DC for Power clamp 400 A		
	99,99 kVAr	10 VA		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
	999,9 kVAr	100 VA		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
	9999 kVAr	1 kVA		$\pm(2\% \text{ of rdg} + 5 \text{ dgt})^1$				
Horse Power ²	9,999 hp	0,001 hp		$\pm(3\% \text{ of rdg} + 5 \text{ dgt})$				
	99,99 hp	0,01 hp		$\pm(3\% \text{ of rdg} + 5 \text{ dgt})$				
	999,9 hp	0,01 hp		$\pm(3\% \text{ of rdg} + 5 \text{ dgt})$				
	9999 hp	1 hp		$\pm(3\% \text{ of rdg} + 5 \text{ dgt})$				
kWh ²	9,999 kWh	0,001 kWh		$\pm(3\% \text{ of rdg} + 5 \text{ dgt})$				
	99,99 kWh	0,01 kWh		$\pm(3\% \text{ of rdg} + 5 \text{ dgt})$				
	999,9 kWh	0,1 kWh		$\pm(3\% \text{ of rdg} + 5 \text{ dgt})$				
	9999 kWh	1 kWh		$\pm(3\% \text{ of rdg} + 5 \text{ dgt})$				

Technical Specification

Measuring function	Measuring range	Resolution	Intrinsic error of digital display at reference condition	Over load capacity	
				Over load value	Overload duration
Ahr	999,9 Ahr	0,1 Ahr	±(3% of rdg+5 dgt)		
Phase angle ²	0°...360°	0,1°	±3°		
Power factor ²	-1...0...1	0,001			
Harmonics (RMS & %) ³	1...13	0,1 V 0,1 A 0,1 %	±(3% of rdg+10 dgt)	1000 VDC/AC 1100 AAC/DC for-Power Clamp 1000A 440 AAC/DC for-Power Clamp400A	Continuously
	14...49		±(5% of rdg+20 dgt)		
THD ³	0...99,9 %	0,1%	±(3% of rdg+20 dgt)		
DF ³	0...99,9 %	0,1 %			
Crest factor ³	1...2,9	0,1	±(2% of rdg+3 dgt)		
	3...5		±(3% of rdg+5 dgt)		
POWER CLAMP1 000A Peak	1400 A / 1400 V	1 A	±(3% of rdg+3 dgt)		
POWER CLAMP 400A Peak	100 A	0,1 A	±(3% of rdg+10 dgt)		
	560 A / 1000 V	1 A / 1 V	±(3% of rdg+3 dgt)		
POWER CLAMP 1000A INRUSH ⁴	999,9 A	0,1 A	±(3% of rdg+5 dgt)		
POWER CLAMP 400A INRUSH ⁴	99,99 A	0,01 A	±(3% of rdg+0.3A)		
	400 A	0,1 A	±(3% of rdg+5 dgt)		
Resistance	9999 Ohm	1 Ohm	±(0.5% of rdg+5 dgt)	1000 V DC/AC eff/Sine wave	10 sec
Continuity	Below 40 Ohm	1 Ohm			
Diode	0...2,2 V	0,001 V			

Note: Accuracy claimed for Power and Current when conductor is positioned at the center of the jaw.

1)For DC A make auto zero correction by long pressing the HOLD key

For Power Clamp 1000A

- 2)Accuracy Defined for $V \geq 10V$ and $I \geq 5A$ Add 10 digit to accuracy when power is < 5.000 kW/kVAr/kVA or < 6.700 hp
- 3)Accuracy Defined for $V \geq 10V$ and $I \geq 10A$
- 4)Accuracy Defined for $I \geq 10A$

For Power Clamp 400A

- 2)Accuracy Defined for $V \geq 10V$ and $I \geq 4A$ Add 10 digit to accuracy when power is < 5.000 kW/kVAr/kVA or < 6.700 hp
- 3)Accuracy Defined for $V \geq 10V$ and $I \geq 10A$
- 4)Accuracy Defined for $I \geq 5A$

For Power Clamp 1000A

- In 1P2W mode maximum power meter can measure is, 1000 kW / 1000 kVAr / 1000 kW / 1341 hp
- In 3P4W mode maximum power meter can measure is, 3000 kW / 3000 kVAr / 3000 kW / 4023 hp
- In 3P3W mode maximum power meter can measure is, 1732 kW / 1732 kVAr / 1732 kW / 2322 hp

For Power Clamp 400A

- In 1P2W mode maximum power meter can measure is, 400 kW / 400 kVAr / 400 kW / 536 hp
- In 3P4W mode maximum power meter can measure is, 1200 kW / 1200 kVAr / 1200 kW / 1608 hp
- In 3P3W mode maximum power meter can measure is, 693 kW / 693 kVAr / 693 kW / 928 hp

AC current measurement in both 1000A and 400A model starts from 0.5A in AC Amp mode and from 1A in LPF mode

Reference conditions for Accuracy

Reference Temperature	23°C ± 2°
Relative Humidity	45%...55% RH
Waveform of measured quantity	Sinusoidal
Input frequency	50 or 60 Hz ±2%
Battery Voltage	8 V ± 0.1 V

Environmental conditions

Operating temperature	0 to +55°C
Storage temperature	-20 to +70°C
Relative humidity	0...75% non condensing
Terminal protection	IP 50 for instrument and IP 20 for terminals
Temp. Coefficient	0.15 X(Intinsic Error) / °C

Battery

Battery voltage	9 V DC
Battery type	Manganese Dioxide, alkaline manganese
Battery life	48 Hrs. Approx.

Display

Display	Seven Segment
Character Height	Main Display Character: 11.5 mm Sub Display Character: 7.2 mm
Number of digits	4 digits
Maximum count	9999 counts For V, I and Power 9999 counts For Resistance
Over range indication	"OL" is displayed
Polarity indication	"—" sign is displayed for negative values.

Applicable Standards

EMC Immunity	ČSN EN 61326-1 ed.2
Immunity	ČSN EN 61010-1 ed.2
Safety	ČSN EN 61010-1 ed.2
IP for water & dust	ČSN EN 60529 – IP 50
Pollution degree	2
Instalation category	CAT IV

Mechanical Configuration

Dimensions 90 x 270 x 70 mm

Weight 0,5 Kg

Sales & service:

METRA BLANSKO s.r.o.
Pražská 7, house No. 2536
678 01 Blansko, Czech Republic

Company reg. No. (IČ): 02356180
Tax reg. No. (DIČ): CZ02356180
Web: www.metra.cz